



# Diesel Generator Set MP-10

## Genset Specification

kVA [Prime]	10
kW [Prime]	8
Engine Make	Mahindra & Mahindra Ltd.
Engine Model	2185 GM C2
Alternator	Stamford or Leroy-Somer
Phase	3-Phase
Voltage [V]	400, 3-Phase
Frequency [Hz]	50
Engine Speed [RPM]	1500
Rated Current [A]	14, 3-Phase
Fuel Tank Capacity [l]	55
Noise Level at 1 m DB(A)	75
Conformance to Standards	ISO 8528
Dimensions (LxWxH) [mm]	1700 x 900 x 1375*
Weight, net [kg]	650

\*high without exhaust pipe and load hook

## Engine

Model	2185 GM C2
Engine Power @ 100% Load [HP]	16.3
Cylinders	2
Displacement in cc	1365
Governing Class	Electric
Starting System [V]	12, Electrical
Cooling System	Water cooled with Radiator
Fuel Consumption @ 100% Load [l/h]	2.9
Fuel Consumption @ 75% Load [l/h]	2.4
Emission class	Stage 3A
Fuel	Diesel

## Alternator

Model	Stamford or Leroy Somer
Type	Brushless, Single Bearing
Power Factor [cos φ]	0.8
Insulation Class	H
Ingress Protection	IP 23



## Control

Make	Deep Sea
Type	Controller 4521
Control	Manual / Automatic - ATS included
Display	LCD
Protection	Engine-High Water Temperature, Low Lube oil pressure, Low Fuel Level, Electrical – Generator Under / Over Voltage, Generator Under / Over Frequency, Generator Over Current, Generator kW Overload



## K&W Drive Systems SRL

Str. Brazilor, nr.74, Brasov, Romania, 500313  
 Mobil: +40728212664  
 Email: kwds@kwds.ro  
 www.stromerzeuger-blackout.com

